



FLEXIBLE PROGRAMMABLE TRANSDUCERIZED NUTRUNNER EN

RRI-BCA SERIES: ANGLE WRENCH

RRI-BCP SERIES: PISTOL SCREWDRIVER

FLEXIBLE PROGRAMMABLE TRANSDUCERIZED NUTRUNNER



Transducerized Pistol Screwdriver & Angle Wrench

Red Rooster cordless transducerized nutrunners are well suited for assembly applications where good torque accuracy is required. 8 Programs can be set for both torque and angular displacement. The programs can be easily selected or programmed in a fixed sequence. The operator receives an audible and visual notification of the judgement


(OK/NG) and the achieved result (torque or angular displacement) is shown on the display. Available in a torque range of 3-60 Nm. Repeatability Cm/Cmk > 2 at +/- 7%.



The programmes can be simply selected or programmed in a fixed sequence.



RRI-BCA Series:
Angle Wrench



Type	Battery voltage (Volt)	WLAN	Drive size	Bolt capacity mm	RPM	Torque Nm	Weight w/o battery kg	Sound level dB(A)	A mm	B mm
RRI-BCA10H2	18V		1/4" 6K	6	150-750	4-10	1,68	< 75	439	38
RRI-BCAW10H2	18V	•	1/4" 6K	6	150-750	4-10	1,68	< 75	439	38
RRI-BCA10S3	18V		3/8" 4K	6	150-750	4-10	1,68	< 75	439	38
RRI-BCAW10S3	18V	•	3/8" 4K	6	150-750	4-10	1,68	< 75	439	38
RRI-BCA16H2	18V		1/4" 6K	6	120-600	5-16	1,68	< 75	439	38
RRI-BCAW16H2	18V	•	1/4" 6K	6	120-600	5-16	1,68	< 75	439	38
RRI-BCA16S3	18V		3/8" 4K	6	120-600	5-16	1,68	< 75	439	38
RRI-BCAW16S3	18V	•	3/8" 4K	6	120-600	5-16	1,68	< 75	439	38
RRI-BCA30S3	18V		3/8" 4K	8	70-350	10-30	1,68	< 75	439	38
RRI-BCAW30S3	18V	•	3/8" 4K	8	70-350	10-30	1,68	< 75	439	38
RRI-BCA50S3	18V		3/8" 4K	10	60-210	20-48	2,16	< 75	535	42,5
RRI-BCAW50S3	18V	•	3/8" 4K	10	60-210	20-48	2,16	< 75	535	42,5
RRI-BCAW50S4	18V	•	1/2" 4K	10	60-210	20-48	2,16	< 75	535	42,5
RRI-BCA60S3	18V		3/8" 4K	10	50-170	25-60	2,16	< 75	535	42,5
RRI-BCAW60S3	18V	•	3/8" 4K	10	50-170	25-60	2,16	< 75	535	42,5
RRI-BCAW60S4	18V	•	1/2" 4K	10	50-170	25-60	2,16	< 75	535	42,5


Battery (2,5 Ah: BB200D-325; 5,0 Ah: BB200D-350) and charger (B84192B) to be ordered separately



RRI-BCPW50RA - This nutrunner was specifically developed for the assembly of cranks in the bicycle industry.

The programmes can be simply selected or programmed in a fixed sequence.

RRI-BCP Series:
Pistol Screwdriver



CHARACTERISTICS

- Brushless motor
- 18 Volt Lithium-Ion battery
- LED status indicates OK - NOK - REVERSE - BATTERY LOW
- Tightening mode setting – Torque or Angle
- Programmable torque
- Programmable angle
- Programmable speed
- Group check / counting
- 8 Programmes including sequence
- Compact and light weight
- The flat battery pack offers stability

Type	Battery voltage (Volt)	WLAN	Drive size	Bolt capacity mm	RPM	Torque Nm	Weight w/o battery kg	Sound level dB(A)	A mm	B mm
RRI-BCP08H2	18V		1/4" 6K	5	220-1100	3-8	1,01	< 75	202,5	240,5
RRI-BCPW08H2	18V	•	1/4" 6K	5	220-1100	3-8	1,01	< 75	202,5	240,5
RRI-BCPW08S3	18V	•	3/8" 4K	5	220-1100	3-8	1,01	< 75	202,5	240,5
RRI-BCP12H2	18V		1/4" 6K	6	150-750	4-12	1,01	< 75	202,5	240,5
RRI-BCPW12H2	18V	•	1/4" 6K	6	150-750	4-12	1,01	< 75	202,5	240,5
RRI-BCPW12S3	18V	•	3/8" 4K	6	150-750	4-12	1,01	< 75	202,5	240,5
RRI-BCP16H2	18V		1/4" 6K	6	100-500	5-16	1,01	< 75	202,5	240,5
RRI-BCPW16H2	18V	•	1/4" 6K	6	100-500	5-16	1,01	< 75	202,5	240,5
RRI-BCP16S3	18V		3/8" 4K	6	100-500	5-16	1,01	< 75	202,5	240,5
RRI-BCPW16S3	18V	•	3/8" 4K	6	100-500	5-16	1,01	< 75	202,5	240,5
RRI-BCP50RA	18V		3/8" 4K	10	30-160	20-48	2,26	< 75	317	240,5
RRI-BCPW50RA	18V	•	3/8" 4K	10	30-160	20-48	2,26	< 75	317	240,5

Battery (2,5 Ah: BB200D-325; 5,0 Ah: BB200D-350) and charger (B84192B) to be ordered separately

FLEXIBLE PROGRAMMABLE TRANSDUCERIZED NUTRUNNER

Transducerized Pistol Screwdriver & Angle Wrench

ACCESSORIES



Charger



Li-Ion Battery



Programming Cable



Side Grip



Battery
Protection Cover



Protection Cover

Type	Order number
Charger (40 min.)	B84192B
Li-Ion Battery 18V 2,5Ah	BB200D-325
Li-Ion Battery 18V 5Ah	BB200D-350
Programming Cable (for BC tool <-> Laptop)	32088-NPA-01
Side Grip for BCP	766-027-612

Type	Order number
Rubber Protection Cover for Battery 18V 2,5Ah	33116-B200D-01
Rubber Protection Cover for Battery 18V 5Ah	33116-B200D-02
Rubber Protection Cover BCP	33116-NPA-01
Rubber Protection Cover BCA 16/30	33116-NRA-01
Rubber Protection Cover BCA 50/60	33116-WRCA-02

Rami Yokota BV

De Ruyterkade 120H
1011 AB Amsterdam

+31 20 531 8805

sales@rami-yokota.com

www.rami-yokota.com



Cordless Tools

